

INVO LIGHT

I. Technical Specifications:

Item Code:	BS1501
Name:	JUMBO STROBE
Volt:	AC 230V, 50Hz
Bulb:	1500W
Circuit Breaker:	16A
Flashing frequency:	2-14/S
TUBE LIFE:	500 hours
Weight:	5.6 kg
Size:	L460X W207 X H136 mm

II. Operational Instructions:

1. Unpack the carton to check if there is any damaged or missing parts when you receive the unit, call the local dealer if anything is found not in a normal condition.
2. Open the lid to install lamp. Keep the lamp untouched by hand and disconnect the unit from power while Re-lamping.
3. Use a clamp to hang the unit onto the truss fasten tight. Tie the unit steadily onto the truss by winding a chain through the bracket of the unit.
4. Place the unit where there is efficient ventilation, away from any flammable and explosive objects.
5. Check that the rated power corresponds to the main supply.

III. Functions:

The 1500W flash tube provides very high rightness . the frequency and brightness is adjustable .it can be controlled by SRC-103 controller up to 8 power strobes in series connection.

IV. Re-lamping:

1. Disconnect from power supply and cool down the unit before re-lamping.
2. Open the lid and replace the burnt-out lamp.
3. Restore the lid.

V. Caution:

1. In order to reach a maximum of safety the following points should be carefully read and observed.
2. Ambient temperature should not exceed 40°C.
3. Disconnect from the power supply before opening or replacement of the lamp and fuse. Please be sure the lamp is cool before replacement!
4. To avoid electrical shock, do not touch any live parts when the unit is activated.
5. Call professionals for maintenance, no spare parts are included with the unit.
6. Lens shall be changed if they have become visibly damaged to such an extent that their effectiveness is impaired, for example by cracks or deep scratches.
7. The lamp shall be change if it has become damaged or thermally deformed.
8. Please ask an approved electrician because of special national requirements for Electro installation. No operation without proof by skilled electrician in public areas!
9. Do not cover the lamp!
10. Alternative precautions to switch off the device shall be taken if it is not easy to reach the socket

