

INVOLIGHT

MUSHROOM

I. Technical Specifications:

Item Code:	MUSHROOM
Volt:	AC 120V/60HZ AC240V/50HZ
Lamp:	OSRAM 64514 120V/300WX2 240V/300WX2
Fuse:	120V/6.3A 240V/5A
Motor:	60RPM/MIN
Colors:	Red, yellow, blue, green, purple and orange
Weight:	5.5Kg
Size:	L415XW320XH320 mm

II. Operational Instructions:

1. Unpack the carton to check if there is any damaged or missing part when you receive the unit, call the local dealer if anything is found not in a normal condition.
2. Open the lid to install lamp. Keep the lamp untouched by hand and disconnect the unit from power while Re-lamping.
3. Use a clamp to hang the unit onto the truss fastens tight. Tie the unit steadily onto the truss by winding a chain through the bracket of the unit.
4. Place the unit where there is efficient ventilation, away from any flammable and explosive objects.
5. Check that the rated power corresponds to the main supply.

III. Re-lamping:

1. Disconnect from power supply and cool down the unit before re-lamping.
2. Open the lid and replace the burnt-out lamp.
3. Restore the lid.

IV. Caution:

1. In order to reach a maximum of safety the following points should be carefully read and observed.
2. Ambient temperature should not exceed 40°C.
3. Disconnect from the power supply before opening or replacement of the lamp and fuse. Please be sure the lamp is cool before replacement!
4. To avoid electrical shock, do not touch any live parts when the unit is activated.
5. Call professionals for maintenance, no spare parts are included with the unit.
6. Lens shall be changed if they have become visibly damaged to such an extent that their effectiveness is impaired, for example by cracks or deep scratches.
7. The lamp shall be change if it has become damaged or thermally deformed.
8. Please be sure to mount luminaries only as shown on the picture below, means hanging on the bracket.
9. Please ask an approved electrician because of special national requirements for Electro installation. No operation without proof by skilled electrician in public areas!
10. Do not cover the lamp!
11. Alternative precautions to switch off the device shall be taken if it is not easy to reach the socket. (e.g. additional disconnection device)