

Controlling:

After having addressed all devices, you may now start operating these via your controller.

DMX PROTOCOL

Channel	Value	Function
1	000-010 011-045 046-080 081-115 116-150 151-185 186-220 221-255	Clustrer control
2		No function
3		Red
4		Green
5		Blue
6		Red/Green
7	000-010 011-255	Strobe
		No Function Strobe 0%-100%
8	000-010 011-024 025-038 039-052 053-066 067-080 081-094 095-108 109-122 123-136 137-150 151-164 165-178 179-192 193-206 207-220 221-250 251-255	Auto Speed
		No Function
		Auto 1
		Auto 2
		Auto 3
		Auto 4
		Auto 5
		Auto 6
		Auto 7
		Auto 8
		Auto 9
		Auto 10
		Auto 11
		Auto 12
		Auto 13
		Auto 14
	Auto 15	
	Auto 16	
	Audio Trigger	

CLEANING AND MAINTENANCE

We recommend a frequent cleaning of the device. Please use a soft lint-free and moistened cloth. Never use alcohol or solvents! There are no serviceable parts inside the device except for the fuse. Maintenance and service operations are only to be carried out by authorized dealers.

Replacing the fuse

If the fine-wire fuse of the device fuses, only replace the fuse by a fuse of same type and rating.

Before replacing the fuse, unplug mains lead.

Procedure:

Step 1: Take out the fuseholder under the power supply.

Step 2: Remove the old fuse from the fuseholder.

Should you need any spare parts, please use genuine parts.

Step 3: Install the new fuse in the fuseholder.

Step 4: Replace the fuseholder in the housing and fix it.

If the power supply cable of this device becomes damaged, it has to be replaced by authorized dealers only in order to avoid hazards.

TECHNICAL SPECIFICATIONS

Power supply: 220 VAC, 50 Hz

Power consumption: 20 W

Number of DMX channels: 8

DMX-512 connection: 3-pin XLR

Sound-control: via built-in microphone via built-in microphone

Maximum ambient temperature Ta: 45° C

Maximum housing temperature TB (steady state): 60° C

Min.distance from flammable surfaces: 0.50 m

Min.distance to lighted object: 0.10 m

Fuse: F 1 A, 250V

Weight: 3 kg

Please note: Every information is subject to change without prior notice.